

CONDUCTOR RANGE OF COPPER WEDGTAP CONNECTORS



For conductor combinations that are not listed in page 9 or where the conductor identities are uncertain, use the following procedure to determine which is the most suitable WEDGTAP. See Table 2.

To use Table 2 apply the following steps:

1. Obtain the diameter of each conductor (main & tap) and refer to columns A & B
2. Add the two diameters together and refer to column C
3. Where the conductor dimensions in columns A, B & C line up horizontally, read across for the appropriate WEDGTAP in column D

EXAMPLE

1. Main: 70mm² HDC Diameter: 10.59mm
Tap: 32mm² HDC Diameter: 8.05mm
These individual diameters can be accommodated across a number of rows.
2. Added together the combined diameter is 18.64mm
This brings the options down to one: WG1C-M,
3. Where there is a selection try the smaller one first

TABLE 2								
DIAMETER OF MAIN CONDUCTOR (mm)		DIAMETER OF TAP CONDUCTOR (mm)		COMBINED DIAMETERS (mm)		WEDGTAP CATALOGUE NUMBER		
MIN	A	MAX	MIN	B	MAX	C	D	
4.47		5.67	4.47		5.67	9.05	10.76	WG1C-S
5.00		8.05	5.00		8.05	10.77	13.05	WG2C-S
5.58		8.85	5.58		8.85	12.80	14.83	WG3C-S
5.58		10.59	5.58		10.59	14.84	16.60	WG4C-S
6.58		10.59	6.58		10.59	16.61	17.65	WG5C-S
8.59		10.59	5.00		7.00	15.59	17.59	WG70C-SH
5.10		12.64	5.10		12.64	17.66	18.69	WG1C-M
6.42		12.64	6.42		12.64	18.70	20.09	WG2C-M
7.38		12.64	7.38		12.64	20.00	21.60	WG3C-M
10.59		12.64	10.59		12.64	21.61	24.00	WG4C-M
11.40		12.64	11.40		12.64	24.01	25.30	WG5C-M

WEDGTAP Kits for bi-metal connections, where the tap conductor is aluminium, are also available. Refer to Pages 11 & 12.



CABLE JOINTS, CABLE TERMINATIONS, CABLE GLANDS, CABLE CLEATS
FEEDER PILLARS, FUSE LINKS, ARC FLASH, CABLE ROLLERS, CUT-OUTS

11KV 33KV CABLE JOINTS & CABLE TERMINATIONS
FURSE EARTHING
www.cablejoints.co.uk
Thorne and Derrick UK

Tel 0044 191 490 1547 Fax 0044 191 477 5371
Tel 0044 117 977 4647 Fax 0044 117 9775582



Formerly Pirelli Cables