

## VOLTAGE DETECTORS

Self Testing Audio / Visual



Tel: +44 (0)191 490 1547  
Fax: +44 (0)191 477 5371  
Email: [northernsales@thorneandderrick.co.uk](mailto:northernsales@thorneandderrick.co.uk)  
Website: [www.cablejoints.co.uk](http://www.cablejoints.co.uk)  
[www.thorneandderrick.co.uk](http://www.thorneandderrick.co.uk)

Salisbury's **Self-Testing Voltage Detectors** allow testing to be continuous and automatic. An intermittent flash and beep confirms the detector is functioning properly.

**Self-Testing Voltage Detectors** are used to verify live or de-energized conductors. These testers may be used with rubber insulating gloves or hot sticks using the splined universal end fitting. Each tester has a 4.5 volt transistor amplifier with a audio/visual indicator. It is recommended that the tester be moved closer to conductor until warning is indicated, or it touches conductor, apparatus, or test point. Test the unit on a nearby energized conductor. To get verification of proper operation set tester on lowest setting. Each tester includes three "C" batteries.



Cat. No.	Dimensions in. ( mm )	Settings phase to phase	Weight ea. lbs. ( kgs )
4544	11 x 3.5 ( 279.4 x 89 )	Off / 240V / 4.2kV / 15kV/25kV/35kV/69kV/115kV/230kV	15oz. ( .43 )
4644	11 x 3.5 ( 279.4 x 89 )	Off / 240V / 4.2kV /35kV/69kV/115kV/230kV/345kV/500kV	15oz. ( .43 )
4744	11 x 3.5 ( 279.4 x 89 )	Off / Test-240V / Battery / URD:15kV/25kV/35kV Overhead: 4.2kV / 15kV/25kV/35kV/46kV/69kV	15oz. ( .43 )
<b>COMPLETE KIT</b>			
4556	1-4544 Tester 240V to 230kV, 1-4315 Case, 1-2500 Shotgun Adapter		2 ( .91 )
4667	1-4644 Tester 240V to 500kV, 1-4315 Case, 1-2500 Shotgun Adapter		2 ( .91 )
4769	1-4744 Tester 240V to 69kV, 1-4315 Case, 1-2500 Shotgun Adapter		2 ( .91 )
4315	12 x 8 x 4.5 ( 5.45 x 3.6 x 2 )	Storage Case	1 ( .45 )
2500		Shotgun Adapter	.4 ( .2 )